

TYPE:	MODEL:
PROJECT:	

## **PRODUCT FEATURES**





Wattage	4.5 W or 5.5 W
Voltage	9 – 15 VAC
Lumens	295 or 389 Lumens
Lamp Туре	MR-16 LED
Housing	Injection-Molded Polymer
Dimensions	5" DIA x 51%" D



## **ORDERING INFORMATION**

EXAMPLE: GW-5277-BSO-4.5-W-36-CFR

CATEGORY	MODEL	FINISH	LED	ACCESSORIES
	5277			

CATEGORY		MODEL	FINISH	LED		ACCESSORIES	
GW	In-Grade	5277	BSO Olde Brass	4.5-W-15	4.5 Watts   Warm   15° Narrow Spot	CFR	Crowned Frosted Lens
СМ	In-Grade Conduit Mount			4.5-W-25	4.5 Watts   Warm   25° Spot	CBL	Crowned Cool Blue Lens
				4.5-W-36	4.5 Watts   Warm   36° Flood	SL	Flat Spread Lens
				4.5-W-60	4.5 Watts   Warm   60° Wide Flood	DBL	Flat Dark Blue Lens
				5.5-W-15	5.5 Watts   Warm   15° Narrow Spot	GL	Flat Dark Green Lens
				5.5-W-25	5.5 Watts   Warm   25° Spot	RL	Flat Red Lens
				5.5-W-36	5.5 Watts   Warm   36° Flood	YL	Flat Amber Lens
				5.5-W-60	5.5 Watts   Warm   60° Wide Flood	HL	Honeycomb louver
				NL	No Lamp		
						ORDERING NOTES	



## **SPECIFICATIONS**

### **HOUSING CONSTRUCTION:**

Injection-molded glass-reinforced polymer.

### LENS COVER CONSTRUCTION:

Die-cast Brass.

#### FINISH:

Olde Brass.

#### LENS:

Clear, tempered glass lens. Optical effect lenses are available.

### **OPTICS/AIMING:**

Lens cover provides 180° of horizontal light distribution. Adjustable lamp bracket provides up to  $\pm 25^\circ$  of tilt as well as 360° rotation of housing for precise beam control. Lamp bracket can be locked into place to prevent disrupting lamp position when relamping.

#### **MOUNTING:**

In-grade. Mounting accessories not required. Conduit mount fixtures have two  $34^{\prime\prime}$  NPT inlets on bottom. Optional concrete mounting kit available.

### **FASTENERS:**

All fasteners are stainless steel.

#### WIRING

Prewired with a 36" pigtail of 18-2 direct-burial cable and underground connectors.

#### **CERTIFICATION:**

UL Listed to U.S. and Canadian safety standards for low voltage landscape luminaires (UL 1838).

### LED:

MR-16 LED Lamp. 295 or 389 Lumens. 4.5 or 5.5 Watts.


#### **ELECTRICAL:**

Input voltage range 9 - 15 VAC. Low voltage transformer required to operate (sold separately).


#### LIGHT DISTRIBUTION:


Very Narrow Spot **15** (15°) Narrow Spot **25** (25°) Medium Flood **36** (36°) Wide Flood **60** (60°)

## **DIMENSIONS**



Top





 $[ \ \, {\sf Conduit \ mount \ (CM) \ option \ shown \ ]}$ 



# www.VistaPro.com $\cdot$ email@vistapro.com $\cdot$ Fax: (888) 670-VISTA (8478)

Front